



USD6

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ccTalk)

Supported bill US\$ 1, 5, 10, 20, 50, 100 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / US\$ 1	OFF	OFF	OFF							
	2 Pulse / US\$ 1	OFF	OFF	ON							
	3 Pulse / US\$ 1	OFF	ON	OFF							
	4 Pulse / US\$ 1	OFF	ON	ON							
	5 Pulse / US\$ 1	ON	OFF	OFF							
	10 Pulse / US\$ 1	ON	OFF	ON							
	20 Pulse / US\$ 1	ON	ON	OFF							
	100 Pulse / US\$ 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms										
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept US\$ 1					ON					
	Reject US\$ 1					OFF					
★	Accept US\$ 5							ON			
	Reject US\$ 5							OFF			
★	Accept US\$ 10								ON		
	Reject US\$ 10								OFF		
★	Accept US\$ 20									ON	
	Reject US\$ 20									OFF	
★	Accept US\$ 50 & 100										ON
	Reject US\$ 50 & 100										OFF

(★) Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P70-USD6/P5(Pulse/ccTalk)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ccTalk Protocol		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Ignore Sensor Problem(Note 1)				ON
★	Acknowledge Sensor Problem(Note 2)				OFF

(★) Manufacture setting

Note:(1) Sensor 6 problem occurred ==>> BA will be still in working order.
(The face LED will be Flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.
(The face LED will be flashing in red.)

DIP SWITCHES SETTING : 3(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Protocol		ON		
★	ccTalk Protocol		OFF		
★	ccTalk Parameters Reset			ON	
	Keep ccTalk Parameters			OFF	
	Ignore Sensor Problem(Note 1)				ON
★	Acknowledge Sensor Problem(Note 2)				OFF

(★) Manufacture setting

Note:(1) Sensor 6 problem occurred ==>> BA will be still in working order.
(The face LED will be Flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.
(The face LED will be flashing in red.)

(3) ccTalk Parameters Reset
Put this switch to on and reset power will restore the ccTalk address to its default value of 40and the encryption key to its default value of 123456.

*This has to be done after finished calibration process.