

**TAO-A Option Switch Settings: 1(Pulse/NISR/ICT/5V Enable)**

**Supported bill MXP 20, 50, 100, 200  
USD 1, 5, 10, 20 8bills.**

TAO-A dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MXP 20 & USD 1	ON											
	Accept MXP 20 & USD 1	OFF											
	Reject MXP 50 & USD 5		ON										
★	Accept MXP 50 & USD 5		OFF										
	Reject MXP 100 & USD 10			ON									
★	Accept MXP 100 & USD 10			OFF									
	Reject MXP 200 & USD 20				ON								
★	Accept MXP 200 & USD 20				OFF								
	Accept Mexico Pesos and US Dollars (Note 1)					ON							
★	Accept Mexico Pesos Only (Note 1)					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / MXP 10									OFF	OFF		
	2 pulses / MXP 10									ON	OFF		
	5 pulses / MXP 10									OFF	ON		
	10 pulses / MXP 10									ON	ON		
★	Interface Timing Conversion	50ms on / 50ms off								OFF	OFF		
		60ms on / 300ms off								ON	OFF		
		30ms on / 50ms off								OFF	ON		
		150ms on / 150ms off								ON	ON		

★ Manufacture setting

Note : (1) For Accepting US Dollars, make sure you have dip 5 set to ON position.

( \* Exchange Rate on USD to MXP is 1:10 )

(2) Reset the bill acceptor after setting the dip switch.

(3) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

**Interface Settings: 2(ICT)**

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT Mode		ON	ON	
	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
★	Reserved			ON	
				OFF	

★ Manufacture setting

**Interface Settings: 2(NISR)**

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	ICT Mode		ON	ON	
★	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
★	Reserved			ON	
				OFF	

★ Manufacture setting

**Interface Settings: 2(Pulse)**

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
		OFF			
	ICT Mode		ON	ON	
	NISR Mode		OFF	ON	
★	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
★	Reserved			ON	
				OFF	

★ Manufacture setting

**Interface Settings: 2(5V Enable)**

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
		OFF			
	ICT Mode		ON	ON	
	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
★	5V Enable Mode		OFF	OFF	
★	Reserved			ON	
				OFF	

★ Manufacture setting