

# **A6/V6 Option Switch Settings : 1**

**Supported bill N\$ 20, 50, 100, 200 4bills.**

A6/V6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject N\$ 20	ON											
Accept N\$ 20	OFF											
Reject N\$ 50		ON										
Accept N\$ 50		OFF										
Reject N\$ 100			ON									
Accept N\$ 100			OFF									
Reject N\$ 200				ON								
Accept N\$ 200				OFF								
Reserved					ON							
Reserved					OFF							
Reserved						ON						
Reserved						OFF						
Harness Disable							ON					
Harness Enable							OFF					
Inhibit Active High								ON				
Inhibit Active Low								OFF				
1 pulse / N\$ 10									OFF	OFF		
2 pulse / N\$ 10									ON	OFF		
4 pulse / N\$ 10									OFF	ON		
20 pulse / N\$ 10									ON	ON		
Pulse Speed		50ms on / 50ms off									OFF	OFF
		60ms on / 300ms off									ON	OFF
		30ms on / 50ms off									OFF	ON
		150ms on / 150ms off									ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

## **A6 Interface Settings: 2**

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	Pulse Mode		ON		
★	RS232 Interface		OFF		
	<b>HOLD</b>			ON	
				OFF	
					ON
					OFF

## **V6 Interface Settings: 3**

	INTERFACE	SW1	SW2	SW3	SW4
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON			
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
	<b>HOLD</b>			ON	
				OFF	
					ON
					OFF

★ Manufacture setting